

μC Based DC Ampere Meter



- DPM-1201 DCA....Size: 96(w)x96(h)x65(d) mm
- DPM-1001 DCA....Size: 96(w)x48(h)x65(d) mm
- DPM-1101 DCA....Size: 72(w)x72(h)x45(d) mm
- DPM-1301 DCA....Size: 48(w)x48(h)x85(d) mm

- Microcontroller based
- 4 Digit display
- Supply 220VAC
- Accuracy of 0.5% of full scale
- Input: 0-75 mili Volt
- Indication resolution as per shunt Ratio
- Shunt Ratio Selectable
- Error Correction @Span current from front key
- Configure link @ Back terminal to avoid unauthentic entry.
- Selectable Shunt Ratio Range: 5.0, 10.0, 20.0, 30.0, 40.0, 50.0, 60.0, 70.0, 80.0, 90.0,
100, 200, 300, 400, 500, 600, 700, 800, 900,
1000, 2000, 3000, 4000, 5000

WAVE INSTRUMENTS LLP

L-45/9, Phase-3, Opp. Mazda Ltd., GIDC Naroda, Ahmedabad -382330, Gujarat – INDIA

☎ +91- 9722003425, ☎ +91-79-40043425, 📞 +91-7043003425.

Email: waveinstruments@gmail.com, Website: <http://www.wavetronics.co.in>