



WTM—192-SEQ

- **WTM-192-SEQ....Size: 192(w)x96(h)x110(d) mm**

- Microcontroller based Single display (1+3 digit)
- Green display for Output Number
- Red Display for count down time
- Supply: 220 VAC
- Output: Relay contact
- Configure after password (Password=100)
- Mode Cycle or Sequence selection
- Power down Memory selection
- On time unit selection (second or Minute)
- OFF time unit selection (second or Minute)
- On time resolution selection (No=1 or Yes=0.1)
- OFF time resolution selection (No=1 or Yes=0.1)
- Number of output required: 1 to 10 settable
- Start selection (Yes=Enable/No=Disable)
- On time 1 to 999 Second or Minute adjustable in set mode
- Off time 1 to 999 second or Minute adjustable in set mode
- 10 LED indication for output

WAVE INSTRUMENTS LLP

L-45/9, Phase-3, Opp. Mazda Ltd., GIDC Naroda, Ahmedabad -382330, Gujarat – INDIA

☎ +91- 9722003425, ☎ +91-79-40043425, 📞 +91-7043003425.

Email: waveinstruments@gmail.com, Website: <http://www.wavetronics.co.in>